



Astronomic In-Wall Programmable Timer with Interchangeable Face Cover

Model No: HET01-H1

Description

The Enerlites Astronomical Timer is used for indoor and outdoor lighting control. This programmable timer switch can store up to 7 unique programs. Its sleek design fits flush with standard wall plates. It works with incandescent, halogen, and LED lighting. The large and easy-to-read LCD screen displays the current day of the week, time, Auto/Manual mode, whether the load is ON or OFF, and if it's in programming mode. This unit also has a built-in rechargeable battery for protection during power outages.

Features

- For use with lights and motors up to 1800-Watts
- No minimum wattage required
- 4 operating modes: manual, automatic, random, count down
- Automatic daylight savings function - no need to reprogram
- Connection: single pole or three-way
- Can also be used like a conventional on/off switch
- 7 customizable settings protected during power outages by built-in back-up battery last up to 14 days
- Random mode adds security when away from home
- 3 interchangeable face covers (white, light almond, and black)

Usage

- Porch lights
- Dwelling scone lights
- Patio lights

Packaging

UPC	883951452452
Retail Box	3"x2.25"x5"
Quantity	1
Master Pack	14"x11"x12.25"
Quantity	40

Specifications

Voltage.....	120VAC @ 60Hz
Resistive.....	15Amp, 1800W
Tungsten	1200W
Ballast	1200VA
LED	150W
Motor	1/2HP

Testing & Code Compliance

- UL/CUL Listed
- California Title 24