



## Wireless Home Automation In-wall Dimmer Switch with Interchangeable Face Cover

**Model No: WF500D**

### Description

Complete your home automation with this Smart Wi-Fi Dimmer Switch. Control your lights with a mobile device and the ENERWAVE App without the added cost of hubs or subscriptions. Schedule your lights, run a timer, create scenes, or check the On/Off status to monitor and save energy. Activate and use voice commands on Alexa or Google Assistant (sold separately) for hands-free control. Provides an easy way to control your home lighting from anywhere.

### Features

- Replaces a standard 120VAC, 15Amp wall switch with a technologically advanced Dimmer switch that can be manually controlled at the device or remotely through Enerwave WiFi App.
- Set scenes, schedule events and even turn ON/OFF. (Program ON/OFF times like a timer).
- Can be used as a Single Pole Dimmer switch or 3- Way (Multi-location) with WF3K Auxiliary Switch (sold separately).
- Manual and Remote ON/OFF or dim any connected lighting
- A blue LED night light can be programmed to come on when the load is ON or OFF.
- 3 Interchangeable Color Face Plates included (white, light almond, and black).
- Use with LED, CFL, fluorescent, incandescent, and halogen bulbs.
- Dimmer will turn on the lights On to the last dim light level

### Testing & Code Compliance

- UL listed, NEC and FCC compliant.

## Specifications

Manufacturer	Enerwave
Included 3 covers	White, Light Almond, and Black
Voltage	120VAC, 60Hz
Maximum load	150W LED, 1500W Incandescent, ½ HP Motor, 1800VA Ballast, 2400W (15A) Resistive
Signal Frequency	WiFi 2.4Ghz
Range	Dependent on Local Internet Wireless Router
Terminations	3 Terminals for Line, Neutral and Ground
Operating Temperature	32°F – 104°F (0°C -40 °C) Indoor Use
Warranty	2 years

### Standards & Compliance

WiFi Certified FCC, Part 15  
Class B UL, CUL Listed