



Wireless Home Automation Control Smart Dual Relay Switch Module

Model No: ZWN-RSM2-Plus

Description

Enerwave ZWN-RSM2-Plus Z-wave Smart Dual Relay Switch Module is a perfect wireless manual and remote on/off switch module to control lighting system. It cannot be used separately but should turn an existing switch into a Z-Wave switch.

This ZWN-RSM2-PLUS module is fully compatible with other Z-wave devices, provide programmable function creating a perfect ambiance such as scenes, association, schedule event, etc. Also it can be added to any Z-Wave compliant controllers. As part of any Z-wave network, each Enerwave device will be manually and/or remotely controlled by commands sent from zwave controllers in real time, but also act as wireless repeater transmitting RF signal from one to another intended device, then extending the range of RF signal all over the system.

Features

- Work with existing light switches, required neutral wire.
- Remote ON/OFF control and/or manual wall switch of any connected lighting fixtures.
- Wireless Z-Wave Plus technology mesh network for command and control interoperability with other Z-Wave compliant controllers.
- Enhance the value and technology of your home.

Specifications

Color	Black
Voltage	120-277 VAC, 50/60Hz
Max Load	10 Amp per load
Signal Frequency	908.42 Mhz
Size	1.63" x1.64" x0.72"
Range	Up to 100 feet in open-air and line of sight distance, depending on obstacles and blocks
Operating Temperature	32°F – 104°F (0°C -40 °C), Indoor Use
Warranty	2 Years

Standards & Compliance

Z-Wave Certified, FCC Part 15, Class B