

Catalog #:	Туре
Project:	Date
Prepared by:	

# Two-Head LED Exit/Emergency Combo Wet & Cold Location



## **DESCRIPTION**

The RXEL25 Series LED Emergency Exit Sign features two heads, single or double faceplate with snap-in & out chevrons. This exit sign uses LED light source and has a backup battery. Ideal for applications requiring quick-installation exit/emergency combo with low energy consumption in wet or cold conditions.

## **DESIGN FEATURES**

#### Construction

- Polycarbonate lens material and waterproof design suitable for wet and cold location
- Flame retardant thermoplastic enclosure
- Universal snap in and out chevrons that meet new state and local laws UL924 codes
- Single or double face plate configuration
- Two fully adjustable round light heads included

#### **Electrical**

- 120/277V AC input, 60Hz
- Operating temperature -13°F (-25°C) to 122°F (50°C)
- Two adjustable lamps included: 180 lms, 0.75W output per head
- · Contains two Ni-Cad battery, 3.6V 1000mAh
- Maximum (1) 1W Remote Heads
- 48 hour recharge after 90 minute discharge
- Manual test switch and LED indicator included

#### Installation

- Housing snaps to canopy with twist and lock
- · Suitable for wall mount, ceiling mount, or end mount
- Universal J-Box mounting pattern on back

#### Remote Head Accessories (Sold Separately)

RH19: Single remote wet listed head

# Dimensions (W x D X H)

• 13" x 2-1/2" x 8-7/8" / height with lamps 13-15/16"

## **Certifications**

- Meets UL924 Listing for wet and cold locations
- Life Safety NFPA 101 Compliant
- State of California Title 20 Compliant
- LED Lamps: 5 Year Limited Warranty
- Other Components: 1 Year Limited Warranty

ORDERIN	G Example: RXEL25RW		
Model #	Finish		
RXEL25			
RXEL25		ettering with White Housing lettering with White Housing	


















# **Photometric**

Model	Lumen output	Spacing distance Wall mount 7.5ft height	Spacing distance Wall mount 10ft height
RXEL25	180lm	26ft	22ft



Compliant NFPA 101 requires 1.0 foot-candle average and 0.1 foot-candle minimum with a 40:1 maximum/minimum ratio.