



In-Wall Programmable Timer

Model No: HET01-W

Description

The Enerlites Timer is used for indoor and outdoor lighting control. This programmable timer switch can store up to 18 unique programs. Its sleek design fits flush with standard wall plates. It works with incandescent, halogen, and LED lighting. The large and easy-to-read LCD screen displays the current day of the week, time, Auto/Manual mode, whether the load is ON or OFF, and if it's in programming mode. This unit also has a built-in rechargeable battery for protection during power outages.

Features

- For use with lights and motors up to 1800-Watts
- No minimum wattage required
- 4 operating modes: manual, automatic, random, count down
- Single Pole switch
- Can also be used like a conventional on/off switch
- 18 customizable settings protected during power outages by
- Built-in back-up battery last up to 7 days
- Bright Blue LED screen for easy programming
- Random mode adds security when away from home

Usage

- Porch lights
- Dwelling scene lights
- Patio lights

Packaging

UPC	883951452452
Retail Box	3"x2.25"x5"
Quantity	1
Master Pack	14"x11"x12.25"
Quantity	40

Specifications

Voltage.....	120VAC @ 60Hz
Resistive.....	15Amp, 1800W
Tungsten	1200W
Ballast	1200VA
LED	150W
Motor	1/2HP

Testing & Code Compliance

- UL/CUL Listed
- California Title 24