



30 Minutes In-Wall Preset Timer Switch

Model No: HET06A-R

Description

Wiring your lights or fan through a preset timer switch like the Enerlites HET06A can help save you money while adding a level of convenience and energy saving to your home. This Enerlites preset timer switch has the time adjustment from 1, 5, 10, 15, 20, and 30 minutes. This unit works with incandescent, fluorescent lamp and fan motor; ideal for closet, pantry, garage, laundry room, basement, outdoor lighting, and home spas.

Features

- Seven buttons preset timer switch.
- For use with incandescent, fluorescent lights, and fan motor.
- Replace standard light or fan single pole switch.
- Sleek design mounts flush with wall plate.
- Blue LED indicator is always on.

Testing & Code Compliance



Specifications

Voltage	120VAC @ 60Hz
Incandescent	800W
Fluorescent	800W
Fan motor	1/4HP
Time delay	1, 5, 10, 15, 20, 30 minutes
Colors Available	White and Ivory

Wiring Diagram

