



## Wireless Home Automation In-wall Dimmer Switch with Interchangeable Face Cover

**Model No: WF3K**

### Description

The WF3K-N 3-Way Control Auxiliary Switch is a companion device designed to work with the WF500D dimmer switch. Alone the WF500D offer dimming at one location, but with WF3K will enable the 3-way or 4-way switching capability. This auxiliary switch does not need to be connected to local WIFI, but it must be used with a WF500D. Use this WF3K 3-Way Auxiliary Switch to reduce energy consumption and provide more convenience to dim at multi-location to you and your family.

### Features

- Replaces a standard 120VAC, 15Amp 3-way wall switch with a technologically advanced auxiliary switch that can be manually controlled at the device and send current status to Enerwave WiFi App.
- Set scenes, schedule events and even turn ON/OFF. (Program ON/OFF times like a timer).
- Can be used as a 3- Way only with WF500D dimmer
- Manual and Remote ON/OFF or dim any connected lighting
- A blue LED night light can be programmed to come on when the load is ON or OFF.
- 3 Interchangeable Color Face Plates included (white, light almond, and black).
- Use with LED, CFL, fluorescent, incandescent, and halogen bulbs.
- Auxiliary switch will turn on the lights On to the last dim light level

### Testing & Code Compliance

- UL listed, NEC and FCC compliant.

## Specifications

Manufacturer	Enerwave
Included 3 covers	White, Light Almond, and Black
Voltage	120VAC, 60Hz
Maximum load	150W LED, 1500W Incandescent, ½ HP Motor, 1800VA Ballast, 2400W (15A) Resistive
Signal Frequency	Auxiliary Switch for WF500D
Range	Dependent on Local Internet Wireless Router
Terminations	3 Terminals for Traveler, Neutral and Ground
Operating Temperature	32°F – 104°F (0°C -40 °C) Indoor Use
Warranty	2 years

### Standards & Compliance

WiFi Certified FCC, Part 15  
Class B UL, CUL Listed