



# 60PAR38/H/FL-120V



**Description** 120V 60W Flood EiKON PAR38 Medium Base  
**Ordering Code** 08143  
**UNSPSC Code** 39101612

## Specifications

<b>Voltage Rating</b>	120
<b>Watts</b>	60
<b>Base Type</b>	Medium Screw (E26)
<b>Bulb Type</b>	PAR38
<b>Filament</b>	CC-8
<b>MOL in/mm</b>	5.31/135.0
<b>MOD in/mm</b>	4.75/120.7
<b>Lumens</b>	810
<b>Approx Initial Max Beam CP</b>	1700
<b>CT deg K</b>	2850
<b>Beam Angle</b>	35°
<b>Rated Life</b>	2,000
<b>Common Code</b>	60PAR38/CAP/FL

watch > like > follow



selection. solutions. simplicity. [eiko.com](http://eiko.com)

23220 W. 84<sup>th</sup> St, Shawnee, KS 66227 · (P) 1.800.852.2217 (F) 1.800.492.8975

Canada: 81 King St, Barrie, ON L4N 6B5 · (P) 1.888.410.8151 (F) 1.888.705.1335