


4RB SERIES

48" Ballast Cover Retrofit Kit



This X1LED retrofit kit is ideal replacement for any 4.25 or 5 inch two light strip to save 40% of energy. Kit includes new ballast cover, unshunted sockets and LED T8 lamps to provide a long life and easily changeable T8 LED lamps. Ballast retrofit kit, 48 in. long, converts an existing strip to carry standard lamps. Material is die-formed 22 gauge steel, with high reflectance baked white enamel finish. TEK screws are provided to attach retrofit ballast cover to an existing channel. The X1LED retrofit kit utilize efficient LED T8 lamps that provide high lumen output with efficient energy savings. Since they don't require any ballast or driver the only component that will ever need changing is the LED T8 lamp. The lamps are warranted for five years. Unlike retrofit kits that utilize LED arrays and drivers these fixtures have the flexibility to change wattage, lumens, and color temperature simply by changing the lamps without the need to call a licensed electrician.

KIT INCLUDES

- (1) 48 in. Ballast cover with lamp holder cut outs
- (1) Ballast mounting plate
- Short Lamp Holders (style & quantity as specified)
- (8) #8 x 3/8" TEX mounting screws

X1 LED

The most economical, practical and user friendly series of LED fixtures with the energy savings, quality of light, long life and hassle-free maintenance. X1 LED fixtures are UL Listed with the latest LED T8 Bypass lamps. Fixtures provide over 44% energy savings over comparable fluorescent fixtures utilizing less expensive fixtures than the fluorescent version (no ballast required) and have flexibility to change wattage and color temperature any time. Fixture performance will evolve over time with the evolution of the T8 LED lamp technology. Concerned about maintenance with an LED array and driver fixture, X1 LED solves that by utilizing a self contained LED lamp that fits into fixture just like a fluorescent lamp.

Lamp Specifications:

- Our T8 LED lamps are available in 2 or 4 ft sizes in different wattage, lumens and color temperature options. See lamp options and specs at www.texasfluorescents.com/X1LEDLamps.
- 50,000 Hour Life with 5 Year Warranty
- Beam Angle 140 Degree
- Aluminum Base and Aluminum Housing with Glass Cover
- Operating Temperature: - 20C to 50C
- Color Temperature: 3500K, 4000K, 5000K
- G13 Pins (Same as Fluorescent Linear T8 Bipin)
- AC100 – 277V without Ballast
- Single Ended or Double Ended Power (If not specified use X1 Single Ended Power)

Optional Dimming Options:

The 4 FT lamps are available with a dimming option. Specially designed dimming lamps require an external driver that runs 2 or 3 lamps. So more than 3 lamps require multiple external drivers. See dimming options and specs at www.texasfluorescents.com/X1LEDdimming.

Emergency Options:

The standard X1 LED Lamps require an inverter or an All-in-one emergency kit that includes LED array, battery and driver. Dimmable T8 LED with external driver works with standard LED EM it. See emergency options and specs at www.texasfluorescents.com/X1LEDemergency.

| ITEM NO. | DESCRIPTION |
|----------------------|---|
| 4RB421T8L11X1LI18W40 | 4.25" Strip Retrofit Kit 48 In. 2100 Lumen Included 1x18W 4000K Lamp |
| 4RB422T8L11X1LI18W40 | 4.25" Strip Retrofit Kit 48 In. 4200 Lumen Included 2x18W 4000K Lamp |
| 4RB501T8L11X1LI18W40 | 5" Strip Retrofit Kit 48 In. 2100 Lumen Included 1x18W 4000K Lamp |
| 4RB502T8L11X1LI18W40 | 5" Strip Retrofit Kit 48 In. 4200 Lumen Included 2x18W 4000K Lamp |

Change 40 to 35 or 50 for different Kelvin. Change Lamp Wattage to 15W on 2FT or 15W on 4FT



| |
|-----------------|
| Catalog Number: |
| Notes: |