

OUTDOOR LED WALL FIXTURE INSTALLATION INSTRUCTIONS

Please read carefully and save these instructions, as you may need them at a later date.

CAUTION

Turn off the main power at the circuit breaker before installing and servicing the fixture, in order to prevent possible shock.

GENERAL

All electrical connections must be in accordance with local and National Electrical Code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections, obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box, and make sure that no parts are missing, by referencing the illustrations on the installation instructions.

ASSEMBLY AND INSTALLATION

1. Thread the 1/8" IPS HEX NUT (3) onto the NIPPLE (4), and screw the NIPPLE (4) into the center hole of MOUNTING BRACKET (2). Do not tighten the HEX NUT (3) at this time. (Fig.1)
2. Pull the power supply wires out from the OUTLET BOX (1), and mount the MOUNTING BRACKET (2) to the OUTLET BOX (1), using MOUNTING SCREWS (5). (Fig.1)
3. Feed the fixture wires (10, 11, 13) through the provided hole on the FOAM PAD (16). Place the FOAMPAD (16) inside the BACK PLATE (6) of the fixture. (Fig.1)
4. Make the following wiring connections (Fig. 1) using the provided WIRE NUTS (14):
WHITE (-) SUPPLY WIRE (9) TO WHITE FIXTURE WIRE (11)
BLACK (+) SUPPLY WIRE (8) TO BLACK FIXTURE WIRE (10)
SUPPLY GROUND WIRE (12) TO FIXTURE GROUND WIRE (13)
5. Place the BACK PLATE (6) of the fixture over the OUTLET BOX (1) and onto the NIPPLE (4), and adjust the NIPPLE (4) until it protrudes out from the BACK PLATE (6) 1/4". Remove the BACK PLATE (6) and secure the position of the NIPPLE (4) by tightening the HEX NUT (3) against the MOUNTING BRACKET (2). Place the BACK PLATE (6) back onto the NIPPLE (4), and secure into place using the THUMB NUT (7) provided. (Fig.1)
6. Apply the FOAM ADHESIVE STRIPS (19) around the inner edge of the DIFFUSER COVER (17). (Fig.2)
7. Attach the DIFFUSER COVER (17) onto the BACK PLATE (6) using the four COVER SCREWS (18). (Fig.1)
8. LED (20), Drive (21)

