

| Job Name/Title: | _Catalog Number | | | |
|-----------------|-----------------|--|--|--|
| Contractor: | Notes: | | | |

LED Exit Signs - NYC Approved

EDGE-LIT RECESSED MOUNT



Easy to Install Safety Solutions for NYC

Topaz's LED Edge-Lit Exit Signs are the ideal safety solution for NYC office, industrial, retail and public places. Always ensure exits are clearly marked, even in the event of a power failure with the built-in 90-minute battery backup. These modern units have a clean look, with clear or mirrored panel and 8" red EXIT letters. Recessed installation is easy with the included bar hangers.

FEATURES

- · New York City approved
- Meets NFPA 70, NFPA 101, UL924, NEC/OSHA Standards
- Battery backup with accessible test button for 90 minutes of illumination during a power outage
- Clear, single face or mirrored, double face configurations available
- Configurable arrows
- · Recessed mount, bar hangers included

SUGGESTED APPLICATIONS

- Office, industrial, retail and other public spaces
- New York City applications

















| Job Name/Title: | _Catalog Number |
|-----------------|-----------------|
| Contractor: | Notes: |

LED Exit Signs - NYC ApprovedEDGE-LIT RECESSED MOUNT

GENERAL SPECIFICATIONS

Input Voltage, Frequency Hz: 120/277V, 60Hz

Emergency Backup: Yes

Emergency Duration / Run Time: 90 minutes

Recharge Time: 24 hours
Recycle Times: 500 cycles
Mounting Height: 7.5 ft to 15 ft
Location Rating: Damp

Ambient Operating Temperature: 50°F to 104°F

Battery Type: 4.8V Ni-Cad¹



ITEM SPECIFICATIONS / ORDER INFO

| Catalog Number | Order Code | UPC | Lumens / Illuminance | Watts | Input Amps 120/277V | Letter Color | Panel Type | Number of Faces |
|--------------------|---------------|--------------|-------------------------|-------|------------------------|-----------------|---------------|-----------------|
| ESEL/SFR/RCL/B-NYC | 71101 | 751338035768 | Average 50 cd/m2 | 3W | 31/14mA | Red | Clear | Single Face |
| ESEL/DFR/RMR/B-NYC | 71102 | 751338035782 | Average 50 cd/m2 | 3W | 31/14mA | Red | Mirrored | Double Face |


NOMENCLATURE

Example: ESEL/SFR/RCL/B-NYC

ESEL = Exit Sign Edge-Lit / SF = Single face R = Recessed Mount / R = Red CL = Clear / B = Battery Backup - NYC = NYC Approved

DF = Double face **MR** = Mirrored

PRODUCT DIMENSIONS / LINE DRAWING



NOTES:

¹On all Exit and Emergency fixtures the battery will be prorated for 5 years.

Specifications subject to change without prior notice.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

WARNING: Some products included in this specification sheet may be subject to the warning requirements of California's Proposition 65. Please refer to your product packaging for more information.

January 2020